

## Automatic Fluxmeter

### Model

KCS-602P

### Function

- Measure the magnetic flux of various magnetic products.

### Peculiarity

- ◆ Manual Zero Manually adjust the drift.
- ◆ Different measuring ranges can be selected.
- ◆ Can be equipped with various types of test coils.
- ◆ Upper and lower limit setting, multiplication factor setting.
- ◆ MCGS Smart Screen, positive and negative polarity are automatically displayed.
- ◆ Data can be saved, queried and exported.



Model	KCS-602P	Serial port	USB
Power	AC.220V	Software	Dedicated software
Warm-up time	3min	Matching coils	Helmholtz coils/ multipole test coils
Max.output curr	0.2、0.5、1、2、4、8 X20Wb	Use environment	10m <sup>2</sup> without dynamic magnetic field or electric field
Displays the valid range	0.01-159.99 mWb	Operating temperature	-5°C~40°C
Calibration accuracy	±1%	Relative humidity	0%~70% (indoors)
Resolution	0.01mWb	Dimensions	W D H 360x370x220
Drift	±1 word 5 seconds	Weight	About 4 KG

充磁、退磁、测量磁

**我们能**

Magnetizing, Demagnetizing, Magnetic measurements, All we can