

Fluxmeter

Model

KCS-602C

Function

- Measure the magnetic flux of various magnetic products.

Peculiarity

- ◆ Manual Zero Manually adjust the drift.
- ◆ Different measuring ranges can be selected.
- ◆ Can be equipped with various types of test coils.
- ◆ 3 ½ digital form, Positive and negative display automatically.



Model	KCS-602C	Serial port	Not
Power	AC.220V	Software	The analog volume can be increased according to requirements
Warm-up time	3min	Matching coils	Helmholtz coils/ multipole test coils
Max.output curr	0.2、0.5、1、2、4、8 X10mWb	Use environment	10m ² without dynamic magnetic field or electric field
Displays the valid range	0.01-19.99 mWb	Operating temperature	-5°C~40°C
Error	±1%	Relative humidity	0%~70% (indoors)
Resolution	0.01mWb	Dimensions	W D H 250x235x110
Drift	±1 word 5 seconds	Weight	About 3 KG

充磁、退磁、测量磁

我们能

Magnetizing, Demagnetizing, Magnetic measurements, All we can